FREQUENCY MANAGEMENT PRODUCT SHORT FORM

KYOCERA AVX

PROUD TO BE A SMALL PART OF MAKING A BETTER WORLD.

QUARTZ CRYSTAL PRODUCTS
METAL CAN PACKAGES

SUMMARY SPECIFICATIONS

CAA Series



Solder Pad Pattern

CA Series



Frequency Range: 3.200 to 75.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
Aging: ±1 PPM to ±3 PPM per Year

CA4 Series



Solder Pad Pattern

Frequency Range: 3.200 to 75.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
Aging: ±1 PPM to ±3 PPM per Year

QUARTZ TUNING FORK PRODUCTS
METAL, CERAMIC & PLASTIC PACKAGES

SUMMARY SPECIFICATIONS

CT26 Series



CT26S Series



CTP3 Series



CTS3 Series



Nominal Frequency: 32.768 KHz Tolerance: ±20 PPM to ±50 PPM at 25° C Stability: Inverse Parabolic Operating Temperature: -20 to 70° C -40 to +85° C Aging: ±3 PPM per Year



To calculate the frequency stability the parabolic curvature constant (K) is needed.

For calculating the stability at 45 ° C?

1- Change in temperature (△T) is (45-25) = +20 ° C

2- Change in frequency is $(-0.035 \times (\triangle ° C)^2)$

$= (-0.035 \times (20)^2 = -14$ PPM

QUARTZ CRYSTAL PRODUCTS
CERAMIC PACKAGES

SUMMARY SPECIFICATIONS

C7S Series 7 x 5 x 1.1



Frequency Range: 8.000 to 133.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
-40 to +105° C
Aging: ±1 PPM to ±3 PPM per Year

C6S Series 6 x 3.5 x 1.2



Frequency Range: 8.000 to 133.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
-40 to +105° C
Aging: ±1 PPM to ±3 PPM per Year

C5S Series 5 x 3.2 x 1



Frequency Range: 8.000 to 133.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
-40 to +105° C
Aging: ±1 PPM to ±3 PPM per Year

C3E Series 3.2 x 2.5 x 0.75



Frequency Range: 12.000 to 52.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
-40 to +105° C
Aging: ±1 PPM to ±3 PPM per Year

C2E Series 2.5 x 2 x 0.6



Frequency Range: 16.000 to 50.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
-40 to +105° C
Aging: ±1 PPM to ±3 PPM per Year

C1E Series 2 x 1.6 x 0.5



Frequency Range: 20.000 to 80.000 MHz
Tolerance: ±10 PPM to ±50 PPM at 25° C
Stability: ±10 PPM to ±100 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
Aging: ±1 PPM to ±3 PPM per Year

C16 Series 1.6 x 1.2 x 0.4



Frequency Range: 24.000, 27.000, 32.000, 36.000, 38.400, and 40.000 MHz
Tolerance: ±10 PPM to ±30 PPM at 25° C
Stability: ±15 PPM to ±50 PPM
Operating Temp: -20 to 70° C
-40 to +85° C
Aging: ±3 PPM per Year

Solder Reflow Profile



CLOCK OSCILLATOR PRODUCTS
CERAMIC PACKAGES

SUMMARY SPECIFICATIONS

S7 Series 7 x 5 x 1.4



Frequency Range: 1.000 to 156.250 MHz
Stability: ±20 PPM to ±100 PPM
Operating Temp: 0 to 70° C, -40 to +85° C, -40 to +125° C
Aging: ±3 PPM per Year

Also available :
32.768 KHz (Real Time Clock)
Low EMI-Spread Spectrum

S5 Series 5 x 3.2 x 1.3



S3 Series 3.2 x 2.5 x 1.2



Frequency Range: 1.000 to 75.000 MHz
Stability: ±20 PPM to ±100 PPM
Operating Temp: 0 to 70° C, -40 to +85° C, -40 to +125° C
Aging: ±3 PPM per Year

S2 Series 2.5 x 2 x 0.95



Frequency Range: 2.000 to 50.000 MHz
Stability: ±20 PPM to ±100 PPM
Operating Temp: 0 to 70° C, -40 to +85° C, -40 to +125° C
Aging: ±3 PPM per Year

HCMOS & TTL CLOCK OSCILLATORS



S7A Series 7 x 5 x 1.4



Frequency Range: 10.000 to 625.500 MHz
Stability: ±25 PPM to ±100 PPM
Operating Temp: 0 to 70° C, -40 to +85° C, -40 to +125° C
Aging: ±3 PPM per Year

S5A Series 5 x 3.2 x 1.3



Frequency Range: 25.000 to 160.000 MHz
Stability: ±25 PPM to ±100 PPM
Operating Temp: 0 to 70° C, -40 to +85° C, -40 to +125° C
Aging: ±3 PPM per Year

LVDS & LVPECL CLOCK OSCILLATORS



VCXO & TCXO CLOCK OSCILLATOR PRODUCTS

CERAMIC PACKAGES

VCXO SUMMARY SPECIFICATIONS

V7 Series 7 x 5 x 1.8



Frequency Range: 1.000 to 52.000 MHz
Frequency Stability: ±25 PPM to ±100 PPM
Voltage Control: ±30 to ±150 PPM Typical
Aging: ±3 PPM per Year Maximum
Operating Temp: 0 to +70°C and -40 to +85°C
Waveform: HCMOS
Voltage: +3.3 V and +5.0 V

V5 Series 5 x 3.2 x 1.2



Frequency Range: 1.000 to 52.000 MHz
Frequency Stability: ±25 PPM to ±100 PPM
Voltage Control: ±30 to ±150 PPM Typical
Aging: ±3 PPM per Year Maximum
Operating Temp: 0 to +70°C and -40 to +85°C
Waveform: HCMOS
Voltage: +3.3 V and +5.0 V

HCMOS VOLTAGE CONTROLLED CLOCK OSCILLATORS

TCXO SUMMARY SPECIFICATIONS

TX32 Series 3.2 x 2.5 x 1.1



Frequency Range: 13.000 to 26.000 MHz
Tolerance: ±1 PPM to ±2.5 PPM
Stability: ±1 PPM to ±2.5 PPM
Aging: ±1 PPM per Year Maximum
Operating Temp: -30 to +80°C
Waveform: Clipped Sinewave
Phase Noise: -110 dBc/Hz at 100 Hz Offset
Voltage: +2.5 V +2.8 V +3.0 V and +3.3 V
Voltage Control: ±4.5 to ±8.5 PPM Typical

TX22 Series 2.5 x 2 x 1



Frequency Range: 13.000 to 26.000 MHz
Tolerance: ±1 PPM to ±2.5 PPM
Stability: ±1 PPM to ±2.5 PPM
Aging: ±1 PPM per Year Maximum
Operating Temp: -30 to +80°C
Waveform: Clipped Sinewave
Phase Noise: -110 dBc/Hz at 100 Hz Offset
Voltage: +2.5 V +2.8 V +3.0 V and +3.3 V
Voltage Control: ±4.5 to ±8.5 PPM Typical

HCMOS AND SINEWAVE TEMPERATURE COMPENSATED CLOCK OSCILLATORS

FREQUENCY CONTROL PRODUCTS
FOR AUTOMOTIVE APPLICATIONS

Certified to Automotive Quality Standard ISO/TS16949.
Superior Shock and Vibration Performance.
Specifically designed to meet the severe environments of automotive products.
Environmentally Friendly Lead-Free/RoHS Compliant Products - ISO14000.
AEC-Q200 Qualified Reliability.

OSCILLATORS

C2 Series 2.5 x 2 x 0.6



C3 Series 3.2 x 2.5 x 0.75



C5 Series 5 x 3.2 x 1.0



C7 Series 7 x 5 x 1.1



Frequency Range: 8 to 150 MHz
Frequency Tolerance : ± 30 PPM to ± 50 PPM at 25°C
Frequency Stability: ± 50 to ± 100 PPM
Operating Temp. Range -40°C to +125°C
Superior Shock and Vibration Resistance
Low Drive Levels from 15 uW to 500 uW
Excellent Thermal Hysteresis
Low Aging

S2 Series 2.5 x 2 x 0.95



S3 Series 3.2 x 2.5 x 1.2



S5 Series 5 x 3.2 x 1.3



S7 Series 7 x 5 x 1.4



Frequency Range: 1 to 156 MHz
Frequency Stability: ±50 PPM to ±100 PPM
Operating Temp. Range: -40 to +125°C
Supply Voltage: +2.5 / +3.3 / +5.0 VDC
Output: HCMOS
Tristate – Enable/Disable
Low Power Consumption
Tight Symmetry of 45/55%

Product	Series	Dimensions (mm)	TPMS	ECU	Sensor	GPS	Airbag	Multimedia	Satellite Radio	RKE
Crystals	C2E	2.5 x 2	✓	✓	✓	✓	✓	✓	✓	✓
	C3E	3.2 x 2.5	✓	✓	✓	✓	✓	✓	✓	✓
	C5S	5 x 32	✓	✓	✓	✓	✓	✓	✓	✓
	C7S	7 x 5	✓	✓	✓	✓	✓	✓	✓	✓
Oscillators	S2	2.5 x 2			✓			✓	✓	
	S3	3.2 x 2.5			✓			✓	✓	
	S5	5 x 3.2			✓			✓	✓	
	S7	5 x 7			✓			✓	✓	

PCB LOGIC CLOCK DESIGN
FOR LOW DPPM (DEFECTIVE PARTS PER MILLION)

APPLICATION NOTES

ASIC manufacturers use an internal oscillator cell. Proper selection of five external capacitors, resistors, and crystal load can increase frequency stability, reduce cost, and reduce dppm.

Two Barkhausen rules are also necessary for oscillation:

- The summation of the phase shifts around a closed loop must be N*360 degrees where N is an integer (0, 1, 2, ...)
- Summation of the gains around a closed loop must be equal to or greater than 1.

Crystal Equivalent Circuit. Fig 1 is the equivalent circuit for a crystal plus external load.

Oscillator Schematic. Most ASIC use the Pierce oscillator configuration. Ref Fig 2.

Pi Capacitors: Pi cap reactance values should be in the low hundreds of ohms and should be approximately equal to the output impedance of the ASIC cell. Oscillator cells designed for lower frequency AT-cut crystals have ~300 to 500 ohms Thevenin output resistance (Rout). Higher frequency fundamentals are ~100 to 300 ohms.

Pi caps are changed as a function of crystal load and VDD. Pi caps are usually the same value or C1 may be slightly smaller than C2. Ref Table I.

Rd selection Rd, sometimes called a phase shift resistor, is between IC output and crystal. The phase shift resistor has 4 functions:

- Reduce crystal power
- Reduce C2 output loading
- Shift phase
- Increase frequency stability

If Rd equals Xc2, a Bode plot would show there is fast rate-of-change of phase at the 360 deg oscillation requirement. Fast rate-of-change of phase is critical for good frequency stability. Ref Fig 3.

Rout and Rd are in series. The series combination is in parallel with C2. Select Rd = Rout = Xc2 unless cell has insufficient drive capability. First select C2, then select Rd.

Rout in series with Rd are shunting C2 (Rout + Rd) // Xc2). With Rd=Rout=Xc2, we have a loaded Q of only 2. Design for Q of 2, but you may accept a Q of 1.

Rf Selection. Most ASIC has internal Rf resistor. If not, choose Rf between 100k and 500k ohms.

Crystal Load. With good oscillator PCB layout and VDD = +5 VDC, Cstray is ~6 to 7 pf. With VDD = +3.3 VDC or lower, Cstray is ~3 pf.

$$Cload = \frac{C1 * C2}{C1 + C2} + Cstray$$

Crystal Load vs Frequency. Crystal load is a function of frequency. Suggested values are in Table II.

C1, C2 Selection. Table III has C1 and C2 calculations for specified loads. Stray capacitance has many variables; however Table III will get most crystals close to frequency.

Circuit Waveshape Verification. Check circuit waveshapes with a non-loading FET probe (or equiv). With Rd=Rout=XC2, top of C2 should be a poorman's sinewave. Peak to peak amplitude should be ~70% of VDD.

If Rd is omitted (sometimes done at higher frequencies or with low output drive), layout should still include Rd as a short. If Rd is a short, top of C2 should be a squarewave with rounded corners. Sharp rise and fall times are indications of excessively high drive or insufficient C2.

If C2 is too small, a low resistance crystal may have high ESR.

$$ESR = Rm * \left(1 + \frac{Co}{Cload}\right)^2$$

Less than full amplitude squarewave is an indication that Rd may be too large or C2 may be too large and is passing signal to ground.

Starting Voltage Checks. Continuously monitor the waveshape at the IC output for any abnormalities during all starting tests. This may be difficult on a PCB unless PCB regulated supply is overridden.

Low voltage starting checks should be made by slowly increasing VDD from 0 volts. Perform this test first to detect and prevent effects of a sleepy crystal. Expect that oscillator should be started at half the nominal VDD. If not, loading on the IC may be too large or the IC may have insufficient gain. Continue this test up to nominal VDD plus 1.5 VDC.

High voltage starting checks are made by applying numerous VDD step functions starting with VDD plus 1.5VDC and slowly decrease to low voltage starting point. Intermittent starting problems may be an indication that Co or Cstray are too large.

Medium voltage starting checks are made by switching the power supply switch on and off. Perform this test from half VDD to VDD plus 1.5 volts.

Negative Resistance Testing. Negative resistance is similar to circuit gain. Test the circuit by installing a resistive pot in series with an AVERAGE crystal. Do not perform this test on a known bad crystal. Negative resistance is the value of the pot plus the crystal's series resistance.

$$-r = Rpot + Rs$$

Crystal Power. While the crystal is disconnected, attach a current probe and measure crystal current. Do not exceed maximum rated power of crystal unit.

$$\text{Crystal Power} = Irms^2 * Rm$$

Adjusting –r. Where gm is the transconductance of the inverter and:

$$-r = gm * \left(\frac{1}{\omega C1} + \frac{1}{\omega C2}\right) \qquad \omega = 2\pi * \text{frequency}$$

By making C1 and C2 smaller, we can raise the negative resistance. Caps too small will cause high ESR and reduced phase shifting.

Circuit Margin. Circuit margin is defined as the absolute value of negative resistance |-r| divided by the average value of ESR.

$$CM = \frac{|-r|}{ESR_{avg}}$$

For low dppm, circuit margins should be at least 10. Some approximate values taken from experimental data can be found in Table III.

Temperature Testing. Quick temperature testing can be performed using a few seconds of freeze mist (or a can of duster spray held upside down) and a hair dryer. Test only when circuit is returning to room ambient.

Summary. Oscillator designers and crystal suppliers working together can assemble circuits having single digit dppm failure rates. This starts with the oscillator being designed on sound basics and working with a crystal supplier, who designs, manufactures and controls his production. On first designs, it is suggested that the schematic or even the PCB should be sent to the crystal supplier for circuit board matching.

CRYSTAL LOAD	+3.3 VDC		+5 VDC	
	C1	C2	C1	C2
6	5	6		
7	8	8		
8	10	10	5	5
10	12	15	6	8
11	15	18	8	10
12	18	22	10	12
14	22	22	15	15
16	22	27	18	22
18	27	33	22	27
20	33	39	27	27
22	39	39	33	33
30	56	56	47	47
32	56	68	47	56

Table 1: C1 & C2 selection for Crystal Load

LOAD	FREQUENCY RANGE
20 PF	---> 5 MHZ
18 PF	5 TO 10 MHZ
16 PF	10 TO 15 MHZ
14 PF	15 TO 20 MHZ
12 PF	20 to 30 MHz
10 PF	30 to 40 MHZ
8 PF	40+ MHZ

Table 2: Suggested Loads for Fundamental Crystals



Figure 1: Equivalent Circuit of a Crystal

CKT MARGIN	EXPECTED DPPM
1.5	Runs poor w/ best xtals
2	Serious operating pblms
3	Intermittent starting
5	~1,000 dppm
10	~100 dppm
15	~25 dppm
20	~15 dppm
25	Single digit dppm

Table 3: Expected DPPM



Figure 2: Oscillators Schematic



Figure 3: Bode Plots with and without Rd

AKER
TECHNOLOGY USA
A DIVISION OF AKER TECHNOLOGY CO., LTD

Proud to be a small part of making a better world.

e-mail: sales@aker-usa.com • www.aker-usa.com

Taiwan Headquarters and Manufacturing
Aker Technology Co., Ltd.
No.11-3, Jianguo Rd., T.E.P.Z ,Tanzih Dist.
Taichung City 427, Taiwan (R.O.C.)
Tel: +886.4.2533.5978
Fax: +886.4.2532.1602
Corporate Website: www.aker.com.tw
Email: info@aker.com.tw

Sales and Customer Support Offices
Taoyuan - Taiwan
14F-B, No.845, Zhongshan Rd
Taoyuan City, Taoyuan County 330, Taiwan (R.O.C.)
Tel: +886-3-3602368
Fax: +886-3-3602278

Shenzhen
Room 28E, Tower C, 6009 Shennan Avenue
Futian District, Shenzhen P.R.C.
Tel: +86-755-82969203
Fax: +86-755-82968070

Shanghai
Room 1103, Les Enphants Fashion Tribe,
No. 1855, Qixin Rd., MinHang Dist.,
Shanghai, 201101, P.R.C.
Tel: +86-21-60676901
Fax: +86-21-60676912

United States
15757 Pines Blvd
Suite 152
Pembroke Pines, FL 33027
Tel: 954.483.4208
Fax: 954.416.6138
Email: info@aker-usa.com